

# SMART 1030

## QUICK REFERENCE CARD

### LIST OF COMMANDS

| PREFIXES |             | DESCRIPTION   |
|----------|-------------|---|
| AT       |             | Attention command which precedes all other commands.  |
| A/       |             | Repeat the last command. Does not require use of AT command.  |
| COMMAND  | PARAMETERS  | DESCRIPTION   |
| A        | NONE        | Answer phone in answer mode without waiting for any rings.  |
| B        | NONE        | Access the bulletin board data base and display listing on screen.  |
| Bx       | x=A..Z      | Dial the phone number of the bulletin board selected.   |
| Dx       | x=0..9TPR,; | Dial a phone number.<br>T=Touch-Tone<br>P=Pulse dial<br>R=Switches modem to answer mode<br>,=Pause<br>;=Return to local command state |
| Ex       | x=0..1      | x=1 Echo back all characters in command state<br>x=0 Do not echo back characters  |
| Gx       | x=0..1      | x=1 ATARI ASCII<br>x=0 ASCII  |
| Hx       | x=0..1      | x=1 Off-hook<br>x=0 On-hook   |
| O        | NONE        | Return to the on-line state.  |
| P        | NONE        | Pulse dialing.  |

# SMART 1030

## QUICK REFERENCE CARD

### LIST OF COMMANDS

| COMMAND | PARAMETERS | DESCRIPTIONS   |
|---------|------------|--|
| Qx      | x=0..1     | x=1 Quiet mode, no result codes sent<br>x=0 Result codes sent.       |
| R       | NONE       | Switches modem to answer mode.                                       |
| T       | NONE       | Touch-Tone dialing.  |
| Vx      | x=0..1     | x=1 Result codes will be numeric<br>x=0 Result codes will be numeric |
| Z       | NONE       | Initialize and reset the modem.                                      |

### RESULT CODES

| NUMERIC | ENGLISH    | MEANING                                 |
|---------|------------|---|
| 0       | OK         | The command has been executed normally. |
| 1       | CONNECT    | A carrier has been detected.            |
| 2       | RING       | The phone is ringing.                   |
| 3       | NO CARRIER | Carrier was lost or never detected.     |
| 4       | ERROR      | An error exists in the command line.    |

**COPYRIGHT 1985  
E & B COMPUTER SERVICES  
P.O. BOX 292506  
COLUMBUS, OHIO 43229**